

# HK1 RBOX X4

## HK1RBOX-X4

Amlogic S905X4

Specifications (adb shell getprop)

```
ro.product.build.fingerprint]:  
[Amlogic/ah212/ah212:11/RQ3A.210805.001.A1/user12212324:user/release-  
keys]  
[ro.product.build.id]: [RQ3A.210805.001.A1]
```

GPU (adb shell dumsys SurfaceFlinger | grep GLES ) :

```
GL ES: ARM, Mali-G31, OpenGL ES 3.2 v1.r25p1-01bet0-6a4488b89-  
0567174f3.3ce44ab07ffe09dde7ee2f5999c7dd83
```

## Backup original ROM

<https://slimboxtv.ru/obnovlenie-proshivki-s-soxraneniem-dannyx-v-usb-burning-tool/>

## Custom ROM

<https://slimboxtv.ru/transpeed-x4-x4s/>

Procedure:

- Start the Amlogic Flash tool with administrative privilege
- Load the custom image

- Leave the options by default (erase flash, etc)
- Press the `start` button
- Push `reset` button located inside the audio/jack connector
- Plug the USB to the PC The USB2 connector (not the blue one) is pretty tight so to avoid bad connection, put the box on the side having the USB port facing the ceiling. Don't move at all during the process.
- Wait for the flash to proceed

# Configuration

- Update Magisk app and system using Magisk app
  - Configure systemless hosts file
  - Configure denylist
- Enable all slimbox features in the `internet` menu
- Install basic packages
  - AdAway
  - Amaze
  - F-Droid
  - Firefox
  - Neo Backup
  - NewPipe
  - Tivimate
  - VLC
  - WG Tunnel
  - Wireguard
- Update all packages
- Freeze APKPure package

```
# Find package name
adb shell pm list packages -e | grep -i apk
# Disable/freeze package
adb shell pm disable com.apkpure.aegon
# Stop all processes
adb shell ps -Aw | grep -i apkpure
# Grab the PID above and kill processes
kill ${PID}
```

- WireGuard Configuration
  - Add the below line in each conf file located in `/data/data/com.wireguard.android/files` : `IncludedApplications = ar.tvplayer.tv`
  - Configure the "Always-on VPN" settings in the "Network & Internet" settings

- Install Viper4Android <https://github.com/programminghoch10/ViPER4AndroidRepackaged>  
Download latest package and install using Magisk.

# Troubleshooting

- Check the current network connections

```
adb shell netstat -lpewt
```

# Infos

<https://androidpctv.com/firmware-hk1-rbox-vontar-x4-transpeed-x4-rom/>

---

Revision #3

Created 10 October 2023 20:34:14 by makwez

Updated 13 October 2023 21:15:12 by makwez